



Reduce your Electric Bills.

100 kVAR

Total capacity

208 V

3-Phase, 60 Hz

12 steps

Individually controlled

1000 A

Suitable facility

MODEL

S-100

Full Load Current

280 A

Operating ambient

Up to 104°F

Dimensions

40" x 60"

Mounting

Floor mounting

Weight Net/Gross

420 / 485 lbs

Sensing

Split core Current Sensor

kVAR Steps

8.32 x 12

Auto-selects the optimal capacitor combinations.

Maintains target power factor in real time.

Individual switching of each capacitor.

Installs at the main panel in under 8 hrs.

Controlled by Celec Digital Power Factor Regulator



Reduced
Electric Bills



Lower Demand
Charges



AI Cloud
Power Logger



Surge
Suppression



Budget
Friendly



www.celec.com

